

SEARS CRAFTSMAN / LIFTMASTER COMPATIBILITY CHART

FOR GARAGE DOOR OPENER CIRCUIT BOARDS AND REMOTES

Use this compatibility chart to see which LiftMaster products will replace a Sears Craftsman garage door part or accessory. If your LiftMaster product has been discontinued, this chart will provide replacement solutions so you don't have to buy a whole new system.

***Note:** The letter at the end of the LiftMaster logic board's part number only represent the date of manufacture.

Example: Part# 41A5021-1G is a more recent model compared to the 41A5021-1E. However, both versions will do the same job.

SEARS MODEL#	SEARS LOGIC BOARD	LIFTMASTER LOGIC BOARD	REMOTE	KEYLESS ENTRY	SECURITY ERA
139.531	41D2742	No Longer Available	61LM	387LMC	8 or 9 Dip Switch
139.5311	41A3066	No Longer Available	61LM	387LMC	8 or 9 Dip Switch
139.532	41D2742	No Longer Available	61LM	387LMC	8 or 9 Dip Switch
139.5321	41A3066	No Longer Available	61LM	387LMC	8 or 9 Dip Switch
139.53225	41A4315-7B	41A4252-7G	81LM	387LMC	Billion Code
139.53225SR	41A4315-7B	41A4252-7G	81LM	387LMC	Billion Code
139.53225SRT	41A4315-7B	41A4252-7G	81LM	387LMC	Billion Code
139.533	41D2742	No Longer Available	61LM	387LMC	8 or 9 Dip Switch
139.5331	41A3066	No Longer Available	61LM	387LMC	8 or 9 Dip Switch
139.53315	41A3625	No Longer Available	61LM	387LMC	8 or 9 Dip Switch
139.53315SR	41A3625	No Longer Available	61LM	387LMC	8 or 9 Dip Switch
139.53325	41A4315-7B	41A4252-7G	81LM	387LMC	Billion Code
139.53325SRT	41A4315-7B	41A4252-7G	81LM	387LMC	Billion Code
139.53335SRT1	41A4315-7B	41A4252-7G	81LM	387LMC	Billion Code
139.534	41D2737	No Longer Available	61LM	387LMC	8 or 9 Dip Switch
139.53403	41A3066	No Longer Available	61LM	387LMC	8 or 9 Dip Switch
139.53413	41A3066	No Longer Available	61LM	387LMC	8 or 9 Dip Switch
139.53415SR	41A3625	No Longer Available	61LM	387LMC	8 or 9 Dip Switch
139.53425	41A4315-7B	41A4252-7G	81LM	387LMC	Billion Code
139.53425SRT	41A4315-7B	41A4252-7G	81LM	387LMC	Billion Code
139.53479	41D4674-3C	41D4674-1G	81LM	387LMC	Billion Code
139.53491	41D4374-9C	41D4674-1G	81LM	387LMC	Billion Code
139.535	41D2737	No Longer Available	61LM	387LMC	8 or 9 Dip Switch
139.53513	41A3063	No Longer Available	61LM	387LMC	8 or 9 Dip Switch
139.53515SR	41A3624	No Longer Available	61LM	387LMC	8 or 9 Dip Switch

SEARS MODEL#	SEARS LOGIC BOARD	LIFTMASTER LOGIC BOARD	REMOTE	KEYLESS ENTRY	SECURITY ERA
139.53525	41A4315-6B	41A4252-6G	81LM	387LMC	Billion Code
139.53525SRT	41A4315-6B	41A4252-6G	81LM	387LMC	Billion Code
139.53535SRT1	41A4315-6D	41A4252-6G	81LM	387LMC	Billion Code
139.536	41D2835	No Longer Available	61LM	387LMC	8 or 9 Dip Switch
139.536006	41D2835	No Longer Available	61LM	387LMC	8 or 9 Dip Switch
139.53601	41D2835	No Longer Available	61LM	387LMC	8 or 9 Dip Switch
139.53602	41D2742	No Longer Available	61LM	387LMC	8 or 9 Dip Switch
139.53603	41D2835	No Longer Available	61LM	387LMC	8 or 9 Dip Switch
139.536036	41D2835	No Longer Available	61LM	387LMC	8 or 9 Dip Switch
139.53604	41D2835	No Longer Available	61LM	387LMC	8 or 9 Dip Switch
139.53605	41A3066	No Longer Available	61LM	387LMC	8 or 9 Dip Switch
139.53606	41A3066	No Longer Available	61LM	387LMC	8 or 9 Dip Switch
139.53607	41A3090	No Longer Available	61LM	387LMC	8 or 9 Dip Switch
139.53608	41A3090	No Longer Available	61LM	387LMC	Billion Code
139.53609	41A3090	No Longer Available	61LM	387LMC	8 or 9 Dip Switch
139.5361	41A3066	No Longer Available	61LM	387LMC	8 or 9 Dip Switch
139.53611	41A3063	No Longer Available	61LM	387LMC	8 or 9 Dip Switch
139.53612	41A3066	No Longer Available	61LM	387LMC	8 or 9 Dip Switch
139.53613	41A3063	No Longer Available	61LM	387LMC	8 or 9 Dip Switch
139.53614SR	41A3625	No Longer Available	61LM	387LMC	8 or 9 Dip Switch
139.536141SR	41A4207-1	No Longer Available	61LM	387LMC	8 or 9 Dip Switch
139.53615SR	41A3625	No Longer Available	61LM	387LMC	check for training button
139.536151SR	41A4207-1	No Longer Available	61LM	387LMC	8 or 9 Dip Switch
139.53618SR	41A3625	No Longer Available	61LM	387LMC	8 or 9 Dip Switch
139.536181SR	41A4207-1	No Longer Available	81LM	387LMC	Billion Code
139.53619SR	41A3625	No Longer Available	61LM	387LMC	8 or 9 Dip Switch
139.536191SR	41A4207-1	No Longer Available	81LM	387LMC	Billion Code
139.53622	41A3066	No Longer Available	61LM	387LMC	8 or 9 Dip Switch
139.53625SR	41A3625	No Longer Available	61LM	387LMC	8 or 9 Dip Switch
139.536251SR	41A4207-1	No Longer Available	81LM	387LMC	Billion Code
139.53626	41A4207	No Longer Available	81LM	387LMC	Billion Code
139.536261	41A4207	No Longer Available	81LM	387LMC	Billion Code
139.536261SR	41A4207	No Longer Available	81LM	387LMC	Billion Code
139.53627	41A4315-6B	41A4252-6G	81LM	387LMC	Billion Code
139.53627SRT	41A4315-6B	41A4252-6G	81LM	387LMC	Billion Code
139.536271SR	41A4315-6B	41A4252-6G	81LM	387LMC	Billion Code

SEARS MODEL#	SEARS LOGIC BOARD	LIFTMASTER LOGIC BOARD	REMOTE	KEYLESS ENTRY	SECURITY ERA
139.53628	41A4315-7B	41A4252-7G	81LM	387LMC	Billion Code
139.53628SRT	41A4315-7B	41A4252-7G	81LM	387LMC	Billion Code
139.53629	41A4315-7B	41A4252-7G	81LM	387LMC	Billion Code
139.53629SRT	41A4315-7B	41A4252-7G	81LM	387LMC	Billion Code
139.53632	41A3625	No Longer Available	61LM	387LMC	8 or 9 Dip Switch
139.53632SR	41A3625	No Longer Available	61LM	387LMC	8 or 9 Dip Switch
139.53635	41A4315-7B	41A4252-7G	81LM	387LMC	Billion Code
139.53635SRT	41A4315-7B	41A4252-7G	81LM	387LMC	Billion Code
139.53636	41A4315-6B	41A4252-6G	81LM	387LMC	Billion Code
139.53636SRT	41A4315-6B	41A4252-6G	81LM	387LMC	Billion Code
139.53637	41A4315-7B	41A4252-7G	81LM	387LMC	Billion Code
139.53637SRT	41A4315-7B	41A4252-7G	81LM	387LMC	Billion Code
139.53638SRT	41A4315-5	41A4252-7G	81LM	387LMC	Billion Code
139.53639	41A3625	No Longer Available	61LM	387LMC	8 or 9 Dip Switch
139.53639SR	41A3625	No Longer Available	61LM	387LMC	8 or 9 Dip Switch
139.5364	41A4315-6B	41A4252-6G	81LM	387LMC	Billion Code
139.53640SRT	41A4315-6B	41A4252-6G	81LM	387LMC	Billion Code
139.53641	41A4315-6B	41A4252-6G	81LM	387LMC	Billion Code
139.53641SRT	41A4315-6B	41A4252-6G	81LM	387LMC	Billion Code
139.53644SRT	41A4315-6D	41A4252-6G	81LM	387LMC	Billion Code
139.53645	41A4315-7B	41A4252-7G	81LM	387LMC	Billion Code
139.53645SRT1	41A4315-7B	41A4252-7G	81LM	387LMC	Billion Code
139.53645SRT3	41A4315-7B	41A4252-7G	81LM	387LMC	Billion Code
139.53646	41A4315-7B	41A4252-7G	81LM	387LMC	Billion Code
139.53646SRT1	41A4315-7B	41A4252-7G	81LM	387LMC	Billion Code
139.53646SRT2	41A4315-7B	41A4252-7G	81LM	387LMC	Billion Code
139.53648	41A4315-7B	41A4252-7G	81LM	387LMC	Billion Code
139.53648SRT1	41A4315-7B	41A4252-7G	81LM	387LMC	Billion Code
139.53648SRT2	41A4315-7B	41A4252-7G	81LM	387LMC	Billion Code
139.5365	41A4315-7B	41A4252-7G	81LM	387LMC	Billion Code
139.53650SRT	41A4315-7B	41A4252-7G	81LM	387LMC	Billion Code
139.53651	41A3625	No Longer Available	61LM	387LMC	8 or 9 Dip Switch
139.53651SR	41A3625	No Longer Available	61LM	387LMC	8 or 9 Dip Switch
139.5366	41A4315-7B	41A4252-7G	81LM	387LMC	Billion Code
139.53660SRT	41A4315-7B	41A4252-7G	81LM	387LMC	Billion Code
139.53660SRT1	41A4315-7B	41A4252-7G	81LM	387LMC	Billion Code
139.53661	41A5021-3	41A5021-1G	971LMC	976LM	Security+ 390 MHz

SEARS MODEL#	SEARS LOGIC BOARD	LIFTMASTER LOGIC BOARD	REMOTE	KEYLESS ENTRY	SECURITY ERA
139.53661SRT	41A5021-3	41A5021-1G	971LMC	976LM	Security+ 390 MHz
139.53661SRT3	41A5021-3D	41A5021-1G	971LMC	976LM	Security+ 390 MHz
139.53662	41A5021-2	41A5021-I	971LMC	976LM	Security+ 390 MHz
139.53662SRT	41A5021-2	41A5021-I	971LMC	976LM	Security+ 390 MHz
139.53662SRT2	41A5021-2	41A5021-I	971LMC	976LM	Security+ 390 MHz
139.53663	41D4674-11	41D4674-10H	971LMC	976LM	Security+ 390 MHz
139.53663SRT	41D4674-11	41D4674-10H	971LMC	976LM	Security+ 390 MHz
139.53663SRT2	41D4674	41D4674-10H	971LMC	976LM	Security+ 390 MHz
139.53664	41A5021-2	41A5021-I	971LMC	976LM	Security+ 390 MHz
139.53664SRT	41A4315-6D	41A4252-6G	971LMC	976LM	Security+ 390 MHz
139.53664SRT1	41A5021-2C	41A5021-I	971LMC	976LM	Security+ 390 MHz
139.53664SRT2	41A5021-2C	41A5021-I	971LMC	976LM	Security+ 390 MHz
139.53669	41A4252-12	41A4252-7G	81LM	387LMC	Billion Code
139.53669SRT	41A4252-12	41A4252-7G	81LM	387LMC	Billion Code
139.5367	41A5021-2	41A5021-I	971LMC	976LM	Security+ 390 MHz
139.53670SRT1	41A5021-2	41A5021-I	971LMC	976LM	Security+ 390 MHz
139.53671	41A5021-3D	41A5021-1G	971LMC	976LM	Security+ 390 MHz
139.53671SRT	41A5021-3D	41A5021-1G	971LMC	976LM	Security+ 390 MHz
139.53671SRT3	41A5021-3D	41A5021-1G	971LMC	976LM	Security+ 390 MHz
139.53672	41A5021-3D	41A5021-1G	971LMC	976LM	Security+ 390 MHz
139.53672SRT	41A5021-3D	41A5021-1G	971LMC	976LM	Security+ 390 MHz
139.53672SRT2	41A5021-3D	41A5021-1G	971LMC	976LM	Security+ 390 MHz
139.53672SRT3	41A5021-3D	41A5021-1G	971LMC	976LM	Security+ 390 MHz
139.53673	41A5021-3D	41A5021-1G	971LMC	976LM	Security+ 390 MHz
139.53673SRT	41A5021-3D	41A5021-1G	971LMC	976LM	Security+ 390 MHz
139.53673SRT3	41A5021-3D	41A5021-1G	971LMC	976LM	Security+ 390 MHz
139.53674	41A5021-3D	41A5021-1G	971LMC	976LM	Security+ 390 MHz
139.53674SRT1	41A5021-3D	41A5021-1G	971LMC	976LM	Security+ 390 MHz
139.53674SRT2	41A5021-3D	41A5021-1G	971LMC	976LM	Security+ 390 MHz
139.53675	41A5021-2	41A5021-I	971LMC	976LM	Security+ 390 MHz
139.53675SRT1		41A5021-I	971LMC	976LM	Security+ 390 MHz
139.53675SRT2	41A5021-2	41A5021-I	971LMC	976LM	Security+ 390 MHz
139.53677	41A5021-3D	41A5021-1G	971LMC	976LM	Security+ 390 MHz
139.53677SRT	41A5021-3D	41A5021-1G	971LMC	976LM	Security+ 390 MHz
139.53677SRT3	41A5021-3D	41A5021-1G	971LMC	976LM	Security+ 390 MHz
139.53678	41A4315-6D	41A4252-6G	81LM	66LM	Billion Code
139.53678SRT	41A4315-6D	41A4252-6G	81LM	66LM	Billion Code

SEARS MODEL#	SEARS LOGIC BOARD	LIFTMASTER LOGIC BOARD	REMOTE	KEYLESS ENTRY	SECURITY ERA
139.53682					Security+
139.53683					Security+
139.53699SR	41A3625	No Longer Available	61LM	65LM	8 or 9 Dip Switch
139-53755			81LM		
139.53759		Call with part number		66LM	Billion Code
139.53778		Call with part number	63LM	65LM	8 or 9 Dip Switch
139-53779	41A4315-6	41A4252-6G	83LM	66LM	Billion Code
139.538	41A4315-6C	41A4252-6G	81LM	66LM	Billion Code
139.53800SRT	41A4315-6C	41A4252-6G	81LM	66LM	Billion Code
139.53824	41A4315-7B	41A4252-7G	81LM	66LM	Billion Code
139.53824SRT	41A4315-7B	41A4252-7G	81LM	66LM	Billion Code
139.53834	41A4315-7D	41A4252-7G	81LM	66LM	Billion Code
139.53834SRT1	41A4315-7D	41A4252-7G	81LM	66LM	Billion Code
139.53834SRT3	41A4315-7D	41A4252-7G	81LM	66LM	Billion Code
139.53855			81LM		
139.53859	41A5021-3G	41A4252-6 (2 LIGHT) 41A4252-7 (1 LIGHT)		66LM	Billion Code
139-53910	41A5021-3	41A5021-1G	971LMC	976LM	Security+ 390 MHz
139.53914	41A5483-5B	41A5483C	971LMC	976LM	Security+ 390 MHz
139.53915SRT	41A4252-6B	41A4252-6G	81LM	66LM	Billion Code
139.53924	41A5483-18	AVAILABLE THRU SEARS ONLY			AVAILABLE THRU SEARS ONLY
139.53927	41A5389-D	41A5389-1E	971LMC	976LM	Security+ 390 MHz
139.53927SRT	41A4252-6B	41A4252-6G	81LM	66LM	Billion Code
139.53954	41A5021-5G	41A5021-I	971LMC	976M	Security+ 390 MHz
139.53960SRT	41A4315-7E	41A4252-7G	81LM	66LM	Billion Code
139.53961	41A5021-3E	41A5021-1G	971LMC	976LM	Security+ 390 MHz
139.53961SRT	41A5021-3E	41A5021-1G	971LMC	976LM	Security+ 390 MHz
139.53962	41A5021-2E	41A5021-I	971LMC	976LM	Security+ 390 MHz
139.53962SRT	41A5021-2E	41A5021-I	971LMC	976LM	Security+ 390 MHz
139.53962SRT1	41A5021-2E	41A5021-I	971LMC	976LM	Security+ 390 MHz
139.53963	41D4674-11E	41D4674-10H	971LMC	976LM	Security+ 390 MHz
139.53963SRT	41D4674-11E	41D4674-10H	971LMC	976LM	Security+ 390 MHz
139.53964	41A5021-4E	41A5021-I	971LMC	976LM	Security+ 390 MHz
139.53964SRT	41A5021-4E	41A5021-I	971LMC	976LM	Security+ 390 MHz
139.53966	41A5021-2E	41A5021-I	971LMC	976LM	Security+ 390 MHz
139.53966SRT	41A5021-2E	41A5021-I	971LMC	976LM	Security+ 390 MHz

SEARS MODEL#	SEARS LOGIC BOARD	LIFTMASTER LOGIC BOARD	REMOTE	KEYLESS ENTRY	SECURITY ERA
139.53966SRT1	41A5021-2E	41A5021-I	971LMC	976LM	Security+ 390 MHz
139.5397	41A4315-7E	41A4252-7G	81LM	66LM	Billion Code
139.53970SRT	41A4315-7E	41A4252-7G	81LM	66LM	Billion Code
139.53971	41A4315-7E	41A4252-7G	81LM	66LM	Billion Code
139.53971SRT	41A4315-7E	41A4252-7G	81LM	66LM	Billion Code
139.53973	41A4315-7E	41A4252-7G	81LM	66LM	Billion Code
139.53973SRT	41A4315-7E	41A4252-7G	81LM	66LM	Billion Code
139.53974	41A5021-3E	41A5021-1G	971LMC	976LM	Security+ 390 MHz
139.53974SRT	41A5021-3E	41A5021-1G	971LMC	976LM	Security+ 390 MHz
139.53975	41A5021-2E	41A5021-I	971LMC	976LM	Security+ 390 MHz
139.53975SRT	41A5021-2E	41A5021-I	971LMC	976LM	Security+ 390 MHz
139.53975SRT1	41A5021-2E	41A5021-I	971LMC	976LM	Security+ 390 MHz
139.53976	41A5021-3E	41A5021-1G	971LMC	976LM	Security+ 390 MHz
139.53976SRT	41A5021-3E	41A5021-1G	971LMC	976LM	Security+ 390 MHz
139.53977SRT	41A5021-3E	41A5021-1G	971LMC	976LM	Security+ 390 MHz
139.53978	41A5021-3E	41A5021-1G	971LMC	976LM	Security+ 390 MHz
139.53978SRT	41A5021-3E	41A5021-1G	971LMC	976LM	Security+ 390 MHz
139.53978SRT1	41A5021-3E	41A5021-1G	971LMC	976LM	Security+ 390 MHz
139.53982SRT	41A5483-2	41A5483C	971LMC	976LM	Security+ 390 MHz
139.53985	41A5483-2B	41A5483C	971LMC	976LM	Security+ 390 MHz
139.5399	41A5483-14	41A5635A	971LMC	976LM	Security+ 390 MHz
139.53990SRT	41A5483-14	41A5635A	971LMC	976LM	Security+ 390 MHz
139.53991	41A5389-B	41A5389-1E	971LMC	976LM	Security+ 390 MHz
139.53991SRT		41A5389-1E	971LMC	976LM	Security+ 390 MHz
139.53992	41A5389-E	41A5389-1E	971LMC	976LM	Security+ 390 MHz
139.53995	41A5483-2	41A5483C	971LMC	976LM	Security+ 390 MHz
139.53995SRT	41A5483-2	41A5483C	971LMC	976LM	Security+ 390 MHz
139.53910D	41A50213H315	41A5021-1M-315	371LMC	377LMC	Security+ 315 MHz
139.53914D	41AB150-2	41AB050-2M	371LMC	377LMC	Security+ 315 MHz
139.53920D	41A5021-3H-315	41A5021-1M-315	371LMC	377LMC	Security+ 315 MHz
139.53930D	41AC150-1	41AC050-1M	371LMC	377LMC	Security+ 315 MHz
139.53985D	41AC150-2	41AC050-2M	371LMC	377LMC	Security+ 315 MHz
139.53990D	41AC175-2A	41AC075-2M	371LMC	377LMC	Security+ 315 MHz
139.53992D	41AS150-1	41AS050-1	371LMC	377LMC	Security+ 315 MHz
139.53993D	41AS150-R2	41AS050-R2	371LMC	377LMC	Security+ 315 MHz
139.53997D	41AC175-2A	41AC075-2A	371LMC	377LMC	Security+ 315 MHz
139.5314D	41AB150	41AB050-2M	371LMC	377LMC	Security+ 315 MHz