

STAR™ 450

COMMERCIAL UNIVERSAL RECEIVER

For Gate and Commercial Door Operators



With **Rapid Learn®** Programs in seconds.
FEATURE

Compact Size; Easy To Program

- Reduces installation time; compact design fits inside most gate operators
- Universal receiver with antenna
- Rapid Learn® feature programs multiple remote controls in just seconds
- User-friendly programming technology makes it easy to add, block and delete up to 450 remote controls
- Ideal for gated communities, parking lots and garages
- Compatible with LiftMaster® Security+® Keyless Entry technologies and Passport™ remote controls
- 315 MHz and 390 MHz
- Duplicate memory module may be removed for programming additional receivers or for safe backup storage



Optional weatherproof accessory box for STAR™ 450 receiver

For more information:
www.devancocanada.com
or call toll free at 855-931-3334

LiftMaster®

STAR™ 450

COMMERCIAL UNIVERSAL RECEIVER

Standard Features

Digital Display

Displays remote control location numbers when programming or access is granted. Also displays user prompts and messages.

Add Key

Used to enter remote control and enter Rapid Learn® mode.

Delete Key

Used to delete a remote control from the selected memory location.

Star Key

Used to enter advanced functions:

- *1 - last remote control received
- *2 - no. of unused memory locations
- *3 - no. of occupied memory locations
- *4 - no. of blocked remote control locations
- *5 - first blocked remote control location
- *7 - software version number
- *0 - audible diagnostics off/on

Antenna Connection

For connection to the direct antenna or the antenna extension kit.

Block Key

Used to block receiver from granting access to the selected remote control. Remote control remains in memory, and may be unblocked in the future.

Numeric Keypad

Used for programming and querying remote control locations. Also used to enter advanced functions.

Pound Key

Used as an escape or exit key for all functions or modes.



STAR™450 315 MHz compatible remote controls

Digital Remote Controls	Passport™ Remotes	Security+® Remotes
361LM	CPT13	370LM
362LM	CPT23	371LM
363LM	CPT33	372LM
333LM	CPT43	373LM
	CPTK13	373P
	CPTK13PH	374LM
	CPTK33	Security+® Keyless Entry
	CPTK33PH	377LM
		379LM

For highest level of security, we recommend the Security+® and Passport® remote control families.

STAR™450 390 MHz compatible remote controls

Digital Remote Controls	Passport™ Remotes	Security+® Remotes
61LM	CPT1	970LM
62LM	CPT2	971LM
63LM	CPT3	972LM
33LM	CPT4	973LM
	CPTK1	Security+® Keyless Entry
	CPTK1PH	976LM
	CPTK1	
	CPTK3PH	
	CPTK3	

For highest level of security, we recommend the Security+® and Passport® remote control families.

STAR™450 optional accessories

Model Number	Description
71-65WTBOX	Plastic Watertight Box
86LM	Antenna Extension Kit
85LM	24VAC Transformer w/Barrel Connector
95LM	24VAC Transformer w/Screw Terminals

LiftMaster®

For more information, visit www.devancocanada.com or call toll free at 855-931-3334



Chamberlain reserves the right to make design or specification changes without notice.
©2010 The Chamberlain Group, Inc. Printed in U.S.A. 8/10 LMCA*450