


P-535T



Open, Close & Stop Transmitter to Control 27 Doors. Match dipswitches 1 thru 5 on both transmitter and receiver. Set the 6th, 7th, & 8th dipswitch in open/close/stop receiver accordingly.

“Changes or modifications not expressly approved by the party responsible for compliance could void the user’s authority to operate the equipment”

| Receiver | Dial Setting 1-9 | Dial Setting ABC | 6th Dipswitch on Receiver | 7th Dipswitch on Receiver | 8th dipswitch on Receiver |
|----------|------------------|------------------|---------------------------|---------------------------|---------------------------|
| Door 1 | 1 | A | “+” | “+” | “+” |
| Door 2 | 2 | A | “+” | “+” | “O” |
| Door 3 | 3 | A | “+” | “+” | “_” |
| Door 4 | 4 | A | “+” | “O” | “+” |
| Door 5 | 5 | A | “+” | “O” | “O” |
| Door 6 | 6 | A | “+” | “O” | “_” |
| Door 7 | 7 | A | “+” | “_” | “+” |
| Door 8 | 8 | A | “+” | “_” | “O” |
| Door 9 | 9 | A | “+” | “_” | “_” |
| Door 10 | 1 | B | “O” | “+” | “+” |
| Door 11 | 2 | B | “O” | “+” | “O” |
| Door 12 | 3 | B | “O” | “+” | “_” |
| Door 13 | 4 | B | “O” | “O” | “+” |
| Door 14 | 5 | B | “O” | “O” | “O” |
| Door 15 | 6 | B | “O” | “O” | “_” |
| Door 16 | 7 | B | “O” | “_” | “+” |
| Door 17 | 8 | B | “O” | “_” | “O” |
| Door 18 | 9 | B | “O” | “_” | “_” |
| Door 19 | 1 | C | “_” | “+” | “+” |
| Door 20 | 2 | C | “_” | “+” | “O” |
| Door 21 | 3 | C | “_” | “+” | “_” |
| Door 22 | 4 | C | “_” | “O” | “+” |
| Door 23 | 5 | C | “_” | “O” | “O” |
| Door 24 | 6 | C | “_” | “O” | “_” |
| Door 25 | 7 | C | “_” | “_” | “+” |
| Door 26 | 8 | C | “_” | “_” | “O” |
| Door 27 | 9 | C | “_” | “_” | “_” |