## **Product Specification Sheet**

## RADIOEM 901

MINI KEYCHAIN RADIO CONTROL TRANSMITTER FIXED CODE (DIP SWITCH)

### STANDARD FEATURES

- 1-button transmitter.
- · Operates 1 door.
- Open/Close function.
- LED indicator.
- Nema 1 enclosure.
- · Approx. 100' range.
- Hand held or keychain attachment.
- Key ring included (not shown).
- Retrofits with any older generation fixed code Manaras-Opera transmitters and receivers.
  No need to change other devices.
- Compatible with most commercial operator brands on the market (in conjunction with RADIORE901).
- FCC/Industry Canada RF Device Approval.

## **OPTIONS (SEE REVERSE)**

 The Series «900» line has been designed for new installations yet is also compatible and can retrofit with any older generation Series «0» Manaras-Opera fixed code (dip switch) radio controls.



- Featuring Innovative Fixed Code Technology
- Improved Product Quality, Reliability and Durability
- Superior Signal Range
- Small Ergonomic Design
- Simplified Pairing and Programming

With a complete re-design, the RADIOEM 901 features the latest fixed code technology, improved reliability and superior range.

Users can control 1 door with single-button open / close functionality providing easy access to any commercial or industrial building.

RADIOEM 901 conveniently retrofits and is compatible with any older generation Manaras-Opera fixed code (dip switch type - Series «0») transmitter or receiver.



# **Product Specification Sheet**

# RADIOEM 901


MINI KEYCHAIN RADIO CONTROL TRANSMITTER FIXED CODE (DIP SWITCH)


### **TECHNICAL SPECIFICATIONS**

Installation:	Hand held or keychain
Technology:	Fixed Code // Dip Switch (10)
No. of Buttons:	1-button
Configuration when used with ECB operators (1):	SBC - Single Button Control (in conjunction with RADIORE901)
Configuration when used with HW operators:	Open/Close Functionality
No. of dip switch Keys:	10 Keys
Housing Materials:	ABS
Protection Class:	Nema 1
Range:	Approx. 100 ft. (30 m)
Power Supply:	12V A23 Battery
Frequency:	313 MHz
Color:	Grey
Retrofit for:	RADIO028
Compatible with:	RADIORE901, RADIORE901A, RADIORE901B, RADIO014, RADIO015

(i) The dip switch Transmitters cannot be paired with the On-Board Radio Receiver. The Series «900» dip switch Transmitters/Receivers are not compatible with Rolling Code Technology.

### **DIMENSIONS**





### OTHER PRODUCTS IN THE SERIES «900»



RADIOEM903 Transmitter 1 Door (3-Buttons) or 1-3 Doors (1-Button)



RADIOEM932 Transmitter 1 to 32 Doors



RADIORE901 Universal Receiver 1 Door



RADIORE901A Universal Receiver 1 Door



RADIORE901B Universal Receiver with Nema 4/12-4X Enclosure and Commercial Antenna



CABLEKIT001 Coaxial Cable 15' and Commercial Antenna